

# Service-Information



Tech.Cust.Service VS-2011      lo-mz	Motorcycles R 50/5 - R 90 S Group: 12	Munich, June '74 1/74 (126 M) e
---	--	------------------------------------

Re.: Generator change-over from 180 to 280 W  
with /6 parts for /5 models

Gentlemen:

As many owners of /5 models are highly interested in changing over from 180 to 280 W generator output we are indicating the parts required in the following:

Quantity	Description	Part No.
1	Threephase generator	12 31 1 357 497
1	Diode chassis	12 31 1 357 498
1	"y" cable	12 33 1 357 639
1	Voltage regulator	12 32 1 358 134
1	Engine protective cover	11 41 1 259 469

Connect the "y" cable to the generator and the diode plate via the two "y" contacts.

When installing the engine protective cover, special attention should be paid to the correct position of the revolution counter drive socket.

Attention:

This refers to R 75/6 - R 90 S

In case of exchange use Regulator 12 32 1 358 134 only for Regulators with the Part No. 12 32 1 357 499.  
The No. 12 32 1 352 472 regulator guard is then no longer needed.

Very truly yours,  
BAYERISCHE MOTOREN WERKE  
Aktiengesellschaft  
n.p.a. i.V.

  
Florent

  
Münzl